SID

ابزارهای
پژوهش

سرویس ترجمه
تخصصی

کارگاه‌های
آموزشی

بلاگ
مرکز اطلاعات علمی

سامانه ویراستاری
STES

فیلم‌های
آموزشی

سامانه ویراستاری (ویرایش متون فارسی، انگلیسی، عربی)

کارگاه‌ها و فیلم‌های آموزشی مرکز اطلاعات علمی

روش تحقیق کمی

آموزش مهارت‌های کاربردی
در تدوین و چاپ مقالات ISI

آموزش نرم افزار Word
برای پژوهشگران

An Antenna-Theory Approach for Modeling Inclined Lightning Return Stroke Channels

R. Moini¹

S.H.H. Sadeghi¹

F. Rachidi²

¹Amirkabir University of Technology – Tehran - Iran

²Swiss Federal Institute of Technology – Lausanne – Switzerland

Abstract – In this paper, we investigate lightning return stroke electromagnetic fields and induced voltages on nearby overhead lines associated with an inclined lightning channel. The study is based on the Antenna Theory (AT) model, which is appropriately extended to take into account channel inclination. Using the AT model, the electromagnetic fields are computed at close, medium and far distance ranges, with respect to an inclined lightning channel. It is shown that the channel inclination affects more markedly the fields at close distances. The induced voltages on a nearby overhead line are also investigated and it is shown that channel inclination could result in a significant variation of the induced voltage magnitudes. It is also shown that, depending on the inclination and its relative position to the observation point or the line, the channel inclination could result either in an increase or in a decrease of the electromagnetic field and induced voltage magnitude.

1. Introduction

Power system apparatus can be adversely affected by the cloud-to-ground lightning return-stroke. The mis-operation failure of such apparatus may not only be due to a direct contact with the lightning discharge, but it is possible to be subjected to an indirect coupling with the lightning channel. The latter case becomes important when the lightning return stroke occurs near distribution networks. This stems from the fact that the resultant over voltage dangerously exceeds the system Basic Insulation Level (BIL) specified in such a voltage level. In addition, electric equipment and information technology systems are at risk through electromagnetic field radiated by the lightning return-stroke.

Lightning is a transient, high-current electric discharge with the height in kilometer range. Cloud-

to-Ground (CG) lightning is less common than the other kinds of lightning (i.e., cloud-to-cloud and interclub lightning), but they are more important for protection studies. The complete discharge, known as flash, has a time duration of about 0.5 second and is made up of various components, including stepped leader, return-strokes, and dart leaders. The part of a flash, which has been of great interest for protection purposes, is the return-stroke phase.

The issue of the lightning return stroke channel modeling has been often discussed and studied in the literature [1 & 2]. One of the basic assumptions in most of the models is that the channel is vertical, while the channel inclination effects have shown to be of great importance when calculating the lightning-induced effects on overhead lines [3]. LeVine and Meneghini studied the effects of the channel tortuosity on the radiated electric and magnetic fields in [4 & 5]. However, their study was limited to far field zone. The channel-inclination effect on lightning-induced voltages was first investigated by Sakakibara [6] who modified the Rusck's model [7] by adding appropriate additional terms in the field-to-transmission line coupling equations. He assumed that the charge density distribution along the leader channel is uniform and the current waveform is triangular. His method has been later extended to a channel with arbitrary configuration by Wu and Hsiao [8].

In this paper, we apply the Antenna theory model for the lightning return stroke channel to investigate the effect of channel inclination. The characteristics of the Antenna Theory model for the vertical return stroke channel has already been presented in [9 & 10]. In this model, the channel is represented as a lossy monopole antenna fed at its base. The return stroke current waveform predicted by the model exhibits dispersion and attenuation while traveling up along the channel, in accordance with available optical observations.

In the first part of the paper, the theoretical basis of the Antenna theory model for the lightning return stroke model is discussed. Then, the expressions for the electromagnetic field originated by a vertical dipole are extended to take into account an arbitrary dipole inclination. Finally the model is applied to investigate the effect of the channel inclination on electromagnetic fields at various distances, and on the induced voltages on nearby overhead lines.

2. Theory

The schematic of the return stroke channel in the vicinity of a metallic structure is depicted in Fig. 1. As shown in this figure, the return stroke channel is modeled by a straight and vertical monopole antenna above a perfectly conducting ground.

Fig. 1: Schematic of the return stroke channel in the vicinity of a metallic structure.

Interest in determining the transient response of antennas and scatterers has grown steadily in recent years. Transients may be dealt both in time or frequency domain. Since the lightning phenomenon provides a narrow pulse, the frequency domain analysis of the problem should be performed for many frequencies, which is a time-consuming process [11]. Additionally, the treatment of non-linearity in frequency domain is not straightforward. Therefore, it is more convenient to use the direct time-domain treatment of electromagnetic problem concerning the lightning aspects. An integral equation developed for determining the time-dependent current distribution on wire structure excited by an arbitrary time-varying electric field is reported in the literature [11]-[12], and will be briefly discussed. The EFIE in the time domain can be solved using the method of moments. A computer code for time-domain solutions has been developed for thin wires in the free space by Van Blaricum [13] and by Landt *et al.* [14]. The University of Limoges group has considered the case of the wire over a lossy ground, where the Van

Blaricum code has been substantially modified to take into account the ground losses [15].

The time-dependent Maxwell's equations furnish the starting point of our derivation. The derivation of the desired integral equation may proceed by the Green's vector identity, which leads to an integral equation relating $\mathbf{J}$ (surface current density) and $\mathbf{E}$ (electric field) on the surface of the conductors under consideration. Assuming that the surface consists in a small circular cross section in comparison with the wavelength, the current density surface integral can be replaced by a line integral along the structure periphery (thin wire approximation). This approach leads to the same result as obtained by adopting the assumption inherent in the thin wire approximation at the beginning. The latter approach is more direct and is the one we employ here.

Fig. 2: Wire structure.

2.1. Formulation of the problem

Consider a filamentary current $\mathbf{I}(\mathbf{r}, t)$ flowing on the path $C(\mathbf{r})$, along which the length variable is s (see Fig. 2). The electric field it produces is given by:

$$\mathbf{E}(\mathbf{r}, t) = -\nabla\Phi(\mathbf{r}, t) - \frac{\partial}{\partial t}\mathbf{A}(\mathbf{r}, t) \quad (1)$$

where

$$\mathbf{A}(\mathbf{r}, t) = \frac{\mu_0}{4\pi} \int_C \frac{\mathbf{I}(\mathbf{r}', t - R/v)}{R} ds' \quad (2)$$

$$\Phi(\mathbf{r}, t) = \frac{1}{4\pi\epsilon_0} \int_C \frac{q(\mathbf{r}', t - R/v)}{R} ds' \quad (3)$$

where $R = |\mathbf{R}| = |\mathbf{r} - \mathbf{r}'|$, v is the velocity of propagation, $\mathbf{r}$ and t denote the observation point location and time, respectively. The primed coordinates $\mathbf{r}'$ and $t' = t - R/v$ denote the source location and time. $\mathbf{s} = \mathbf{s}(\mathbf{r})$ and $\mathbf{s}' = \mathbf{s}(\mathbf{r}')$ denote the unit tangent vectors to $C(\mathbf{r})$ at $\mathbf{r}$ and $\mathbf{r}'$, respectively. The

differential operators in (1) are with respect to the observation coordinates. The required terms in Eq. (1) can be written as:

$$\frac{\partial}{\partial t} \mathbf{A}(\mathbf{r}, t) = \frac{\mu_0}{4\pi} \int_C \frac{\mathbf{s}'}{R} \frac{\partial}{\partial t'} I(\mathbf{r}', t') ds' \quad (4)$$

$$\nabla \Phi(\mathbf{r}, t) = \frac{1}{4\pi\epsilon_0} \times \int_C \left[-q(\mathbf{r}', t') \frac{\mathbf{R}}{R^3} + \frac{\mathbf{R}}{R^2 v} \frac{\partial}{\partial s'} I(\mathbf{r}', t') \right] ds' \quad (5)$$

Combining (4) and (5) with (1), one obtains the integral representation for the electric field due to a filamentary current [11],[17]:

$$\mathbf{E}(\mathbf{r}, t) = -\frac{\mu_0}{4\pi} \int_C \left[\frac{\mathbf{s}'}{R} \frac{\partial}{\partial t'} I(s', t') + v \frac{\mathbf{R}}{R^2} \frac{\partial}{\partial s'} I(s', t') - v^2 \frac{\mathbf{R}}{R^3} q(s', t') \right] ds' \quad (6)$$

Equation (6) is valid at every time and every position in space except for the immediate source region. Such region consists of a conductor of nonzero cross section, with $|\mathbf{r} - \mathbf{r}'| \geq a(r')$, "a" being the wire radius at $\mathbf{r}'$. Assuming that $I(s', t')$ and $q(s', t')$ are confined to the conductor axis (thin wire approximation), the boundary condition on the tangential electric field for a perfect conductor wire is:

$$\mathbf{s} \cdot [\mathbf{E}^s + \mathbf{E}^i] = 0 \quad (7)$$

where $\mathbf{E}^i$ is the applied field which induces the current I generating the scattered field $\mathbf{E}^s$. By applying this boundary condition to the tangential electric field at the conductor surface in Eq. (6), one can obtain the time-dependent electric field integral equation for thin conducting wires in the following form:

$$\mathbf{s} \cdot \mathbf{E}^i(\mathbf{r}, t) = \frac{\mu_0}{4\pi} \int_C \left[\frac{\mathbf{s} \cdot \mathbf{s}'}{R} \frac{\partial}{\partial t'} I(s', t') + v \frac{\mathbf{s} \cdot \mathbf{R}}{R^2} \frac{\partial}{\partial s'} I(s', t') - v^2 \frac{\mathbf{s} \cdot \mathbf{R}}{R^3} q(s', t') \right] ds \quad (8)$$

$\mathbf{r} \in C(\mathbf{r}) + \mathbf{a}(\mathbf{r})$

where

$$q(s', t') = - \int_{-\infty}^{\infty} \frac{\partial}{\partial s'} I(s', \tau) d\tau \quad (9)$$

Since the integration path in Eq. (8) is along $C(\mathbf{r})$, while the wire radius displaces the field evaluation path, R is always positive and therefore the integral in Eq. (8) has no singularity. Eq. (8) is the integral equation whose solution can be sought using the method of moment. If the wire structure under consideration is located over a perfect conducting ground, the image theory is used, in order to take into consideration the effect of the ground. Fig. 4 shows an incremental section of the wire structure above a perfect ground. In this case Eq. (8) will change to

$$\mathbf{s} \cdot \mathbf{E}^i(\mathbf{r}, t) = \frac{\mu_0}{4\pi} \int_C \left[\frac{\mathbf{s} \cdot \mathbf{s}'}{R} \frac{\partial}{\partial t'} I(s', t') + v \frac{\mathbf{s} \cdot \mathbf{R}}{R^2} \frac{\partial}{\partial s'} I(s', t') - v^2 \frac{\mathbf{s} \cdot \mathbf{R}}{R^3} q(s', t') - \frac{\mathbf{s} \cdot \mathbf{s}^*}{R^*} \frac{\partial}{\partial t^*} I(s', t^*) - v \frac{\mathbf{s} \cdot \mathbf{R}^*}{R^{*2}} \frac{\partial}{\partial s^*} I(s', t^*) + v^2 \frac{\mathbf{s} \cdot \mathbf{R}^*}{R^{*3}} q(s', t^*) \right] ds' \quad (10)$$

where

$$R = \sqrt{(s - s')^2 + a^2}, \quad t' = t - R/v$$

$$R^* = \sqrt{(s - s'^*)^2 + a^2}, \quad t'^* = t - R^*/v$$

s'^* is the image point of a source s' , s'^* and $\mathbf{s}^*$ are the corresponding unit vectors.

2.2. Numerical Considerations

The method of moments (MoM) [15] is used to solve the integral equation given in Eq. (10). In this regard, we first divide the thin wire into N_s elementary segments of length Δ_i while the time span is divided into N_t equal steps of length Δ_t . Then, a set of rectangular basis functions is defined for expressing the known current in each segment, i.e.,

$$I(s_0, t_0) = \sum_{i=1}^{N_s} \sum_{j=1}^{N_t} I_{ij}(s_i'', t_j'') U(s_i'') V(t_j'') \quad (11)$$

$$s_i'' = s_0 - s_i$$

$$t_i'' = t_0 - t_i$$

$$U(s_i'') = \begin{cases} 1 & |s_i''| \leq \Delta_i/2 \\ 0 & \text{otherwise} \end{cases} \quad (12)$$

$$V(t_i'') = \begin{cases} 1 & |t_i''| \leq \Delta_t/2 \\ 0 & \text{otherwise} \end{cases}$$

A second-order polynomial representation is used to evaluate $I_{ij}(s_i'', t_j'')$ and the interpolation is chosen to be Lagrangian:

$$I_{ij}(s_i'', t_j'') = \sum_{l=-1}^{+1} \sum_{m=v}^{v+2} B_{ij}^{(l,m)} I_{i+1,j+1} \quad (13)$$

with

$$B_{ij}^{(l,m)} = \prod_{p=-1}^{+1} \prod_{q=v}^{v+2} \frac{(s_o - s_{i+p})(t_o - t_{j+q})}{(s_{i+1} - s_{i+p})(t_{j+m} - t_{j+q})} \quad (14)$$

$$\begin{cases} v = -1; & \Delta R = \frac{R}{c(t_j - t_{j-1})} > 0.5 \\ v = -2; & \Delta R < 0.5 \end{cases} \quad (15)$$

$I_{i+1,j+m}$ is the current value at the center of the (i+1)th space segment and the (j+m)th time step.

The last step of the method of moment consists of choosing the test function in order to obtain a system of linear equations [15]. The point matching method, based on Dirac distributions, i.e.,

$$\begin{aligned} \delta(t - t_u) & \quad \text{in the space} \\ \delta(t - t_v) & \quad \text{in the time} \end{aligned} \quad (16)$$

is used. We then obtain the following system of equations:

$$(I_{iv}) = (Z_{uv})^{-1} \{ (e_{uv}^a) - (e_{ux}^d) \}; \quad (17)$$

$$\begin{aligned} i &= 1, \dots, N_s; \quad u = 1, \dots, N_s; \\ v &= 1, \dots, N_T; \quad x = 1, \dots, v-1 \end{aligned}$$

where $I_{i,v}$ is the unknown vector at every time step $v\Delta t$, and (Z_{iu}) is the matrix of the mutual interactions between the segments with the advantage of being time independent. This system of linear equations is solved step by step in time.

2.3. The Antenna Theory Model

In the antenna theory (AT) model, the return-stroke channel is considered as a lossy vertical antenna fed by a voltage source at its lower end. The voltage of the source is given by the following equation [10-11]:

$$V(t) = F^{-1} [Z(f)] * I(0,t) \quad (18)$$

where $I(0,t)$ is the current at the channel base, $Z(f)$ is the input impedance of the monopole antenna and F^{-1} and $*$ denote inverse Fourier transform and the convolution integral operator respectively. $Z(f)$ can be calculated applying the MoM to the EFIE, which is a function of the length, radius and distributed resistance of the channel.

To reduce the propagation speed of the current wave in the AT model to a value consistent with observations, $v < 3 \times 10^8$ m/s, we use $\epsilon > \epsilon_0$ in calculating the current variation along the channel,

and then use that current distribution to calculate the electromagnetic fields radiated by the antenna in free space ($\epsilon = \epsilon_0$). The arbitrary increasing of ϵ in determining the channel current distribution serves to account for the fact that channel charge is predominantly stored in the radial corona sheath whose radius is much larger than that of the channel core which carries the longitudinal channel current, resulting in $v < 3 \times 10^8$ m/s. This simulates an increase of shunt capacitance per unit antenna length due to corona. The use of $\epsilon > \epsilon_0$ additionally introduces the effect of radiation into the fictitious medium, but the resultant current distribution along the channel is unlikely to differ significantly from the case of no such effect (the transmission line current is expected to dwarf the antenna current). An alternative approach to modeling corona effect on propagation speed would be to introduce capacitive antenna loading. Ohmic losses in the antenna further reduce v , but for the selected value of resistance per unit length, this additional reduction in v is expected to be relatively small.

In the AT model, there are only two parameters to be adjusted, namely, the propagation speed v for the case of nonresistive antenna and the value of distributed resistance R . The value of resistance per unit length is selected (by trial and error) to provide an agreement between model-predicted and measured electric fields at close distances.

Applying the MoM to Eq. (10) with the AT model assumptions provides the current distribution on RSC and on any nearby metallic structures [15]. As a result, it is possible to directly include such structures in the modeling stage of the RSC, providing an effective means for the study of lightning-related problems.

3. Electromagnetic field calculation

In the case of the monopole antenna model for the lightning return stroke channel, there is a voltage source at the base of the channel. Applying Eq. (10) to the waveform of this voltage source and solving the proposed electric field integral equation by the method of moments, the current distribution is calculated. The electromagnetic field produced by a vertical infinitesimal dipole, located on and oriented along the z axis has already been presented in [16].

Now, consider an infinitesimal dipole which is located at $P'(x', y', z')$ with an arbitrary orientation defined by the following unit vector (see Fig. 3):

$$\mathbf{n} = \cos \alpha \hat{\mathbf{a}}_x + \cos \beta \hat{\mathbf{a}}_y + \cos \gamma \hat{\mathbf{a}}_z \quad (19)$$

Fig. 3: An infinitesimal dipole with arbitrary orientation.

In order to calculate the induced electromagnetic fields at a given point P, the relations presented in [16] can be generalized to this case as shown in Eqs. (20-27):

$$dE_x(P, t) = \cos \alpha dE_{h0}(P, t) + \frac{x_0 - x_1}{r} dE_{v0}(P, t) \quad (20)$$

$$dE_y(P, t) = \cos \beta dE_{h0}(P, t) + \frac{y_0 - y_1}{r} dE_{v0}(P, t) \quad (21)$$

$$dE_z(P, t) = \cos \gamma dE_{h0}(P, t) + \frac{z_0 - z_1}{r} dE_{v0}(P, t) \quad (22)$$

in which,

$$dE_{h0}(P', t) = \frac{d\ell}{4\pi\epsilon_0} \left[\frac{3rh}{R^5} \int_0^t i(P', \tau - R/c) d\tau + \frac{3rh}{cR^4} i(P', t - R/c) + \frac{rh}{c^2 R^3} \frac{\partial i(P', t - R/c)}{\partial t} \right] \quad (23)$$

$$dE_{v0}(P, t) = \frac{d\ell}{4\pi\epsilon_0} \left[\frac{2h^2 - r^2}{R^5} \int_0^t i(P', \tau - R/c) d\tau + \frac{2h^2 - r^2}{cR^4} i(P', t - R/c) - \frac{r^2}{c^2 R^3} \frac{\partial i(P', t - R/c)}{\partial t} \right] \quad (24)$$

and,

$$dH_x(P, t) = \left(\frac{z_0 - z_1}{r} \cos \beta - \frac{y_0 - y_1}{r} \cos \gamma \right) dH_{\phi 0}(P, t) \quad (25)$$

$$dH_y(P, t) = \left(\frac{x_0 - x_1}{r} \cos \gamma - \frac{z_0 - z_1}{r} \cos \alpha \right) dH_{\phi 0}(P, t) \quad (26)$$

where,

$$dH_{\phi 0}(P, t) = \frac{d\ell}{4\pi} \left[\frac{r}{R^3} i(P', t - R/c) + \frac{r}{cR^2} \frac{\partial i(P', t - R/c)}{\partial t} \right] \quad (27)$$

In these equations, dE_{h0} , dE_{v0} , and $dH_{\phi 0}$ are the electromagnetic fields radiated by a vertical infinitesimal dipole, $d\ell$ is the length of the dipole, R is the distance between the dipole and the observation point, and c is the speed of light. The sign of h is assumed to be positive if $\mathbf{n}$ and $P'N$ have the same direction and negative if they are in opposite direction. Thus, the total electromagnetic fields at point P caused by a current which is flowing in a wire can be calculated by dividing the wire into segments and adding the contribution of each segment.

4. Results

In order to illustrate the capability of the Antenna Theory model to predict the effects of the inclination of the channel, two problems have been studied. In the first one, the electromagnetic fields at different locations with respect to an inclined channel are calculated at different distances from the channel. The second concerns the calculation of overvoltages in an overhead line located nearby the return stroke channel.

4.1. Electromagnetic Fields

Consider a straight return stroke channel which is located in the yz plane and makes an angle of $\theta = 30^\circ$ with the z axis (Fig. 4). According to the Antenna Theory model this channel is modeled as a monopole antenna which is fed at its base and radiates in the free space. Once the current distribution along the antenna is known using the electric field integral equation, the electromagnetic fields at any distance from the channel can be computed. Fig. 5 shows the channel base current and the radiated electromagnetic fields are plotted in Fig. 6 for different observation points and distances from the channel. At close distances, (Fig. 6.a & 6.b) the effect of the inclination is clearly observed. At $t = 50\mu s$, the value of the electric field at point C (over which the channel is bending) is almost doubled with respect to the vertical channel. At this range, the maximum value of the magnetic field has markedly increased due to the channel inclination.

At medium distance ranges (Figs. 6.c & 6.d), the electric field shows the typical increasing ramp at all points. At point C, the steepness of this ramp is three times greater than that of the vertical channel and the magnetic field shows a hump which is more apparent at this point. At far distances (Figs. 6.e and 6.f), the

effect of the channel inclination on the

Fig. 4: The inclined channel and the observation points.

4.2. Induced Overvoltages in an Overhead Line

Consider a single-phase overhead line located in the vicinity of the return stroke channel, as shown in Fig. 7. The height of the wire is 10 m and the length of the line is 1 km. The line is matched at both ends. Fig. 8 depicts the induced overvoltages at the line extremity, computed using the AT model. The channel inclination makes an angle $\theta = 30^\circ$ with respect to the vertical axis. We have considered 3 channel orientations (defined with the azimuth angle ϕ):

- $\phi = 0^\circ$, corresponding to an inclination parallel to the line (channel contained in the xz plane),
- $\phi = 90^\circ$ corresponding to a channel inclination towards the line, and
- $\phi = -90^\circ$ corresponding to a channel inclination towards the opposite direction of the line.

It can be seen from Fig. 8 that for the considered cases, the channel inclination produces a variation in the induced voltage magnitude of about $\pm 35\%$ with respect to the one caused by a vertical channel. The maximum increase in the magnitude occurs for an inclined channel oriented towards the line ($\phi = 90^\circ$), in agreement with the results presented in [6]. However, other channel orientations (e.g. $\phi = 0^\circ, -90^\circ$)

may result in a decrease of the magnitude of the induced voltages, with respect to the one corresponding to a vertical channel.

5. Conclusion

In this paper, the Antenna Theory model for the lightning return stroke channel is applied to the case of an inclined channel. This model is based on

electromagnetic fields appears to be less important.

Fig. 5: The channel base current.

solving the electric field integral equation in time domain using the method of moments. The well-known analytical expressions for the electromagnetic field originated by a vertical dipole have been extended to take into account dipole inclination.

Using the AT model, the electromagnetic fields are computed at close, medium and far distance ranges, with respect to an inclined lightning channel. It is shown that the channel inclination affects more markedly the fields at close distances.

The Antenna Theory model, in addition to modeling the return stroke, is able to compute the inducing effects of the return stroke on any wire structure located in the vicinity of the channel. The analysis of induced voltages on a nearby overhead line shows that channel inclination could result in a significant variation of the induced voltage magnitudes.

It is also shown that the channel inclination could affect very differently the field and induced voltage magnitudes. Indeed, depending on the channel orientation and its relative position to the observation point or to the line, the channel inclination could result either in an increase or in a decrease of the electromagnetic field and induced voltage magnitude.

Fig. 7: The relative location of an overhead line by an inclined lightning channel.

a) Electric field, $r = 500$ m.

b) Magnetic field, $r = 500$ m.

c) Electric field, $r = 5$ km.

d) Magnetic field, $r = 5$ km.

e) Electric field, $r = 100$ km.

f) Magnetic field, $r = 100$ km.

Fig. 6: The vertical component of electric field and the angular component of magnetic field at different distances from the channel and different observation points (A, B, and C as specified in Fig. 4).

Fig. 8: A comparison between the induced voltages at the end of the line for different orientation of the channel.

References

- [1] V.A. Rakov and M.A. Uman, "Review and evaluation of lightning return stroke models including some aspects of their application," *IEEE Trans. EMC*, Vol. 40, No. 4, pp. 403-426, 1998.
- [2] C.A. Nucci, G. Diendorfer, M.A. Uman, F. Rachidi, M. Ianoz, and C. Mazzetti, "Lightning return stroke current models with specified channel base current: A review and comparison," *J. Geophys. Res.*, Vol. 95, No. D12, pp. 20395-20408, 1990.
- [3] K. Michishita, M. Ishii, and Y. Hongo, "Induced voltage on an overhead wire associated with inclined return-stroke channel-model experiment on finitely conductive ground," *IEEE Trans. EMC*, Vol. 38, No. 3, pp. 507-513, Aug. 1996.
- [4] D.M. LeVine and R. Meneghini, "Simulation of radiation from lightning return strokes: The effects of tortuosity," *Radio Science*, Vol. 13, No. 5, pp. 801-809, 1978.
- [5] D.M. LeVine and R. Meneghini, "Electromagnetic fields radiated from a lightning return stroke: Application of an exact solution to Maxwell's equations," *Journal of Geophysical Research*, Vol. 83, No. C5, pp. 2377-2384, 1978.
- [6] A. Sakakibara, "Calculation of induced voltages on overhead lines caused by inclined lightning studies," *IEEE Trans. Power Delivery*, Vol. 4, No. 1, pp. 683-693, Jan. 1989.
- [7] S. Rusck, "Induced lightning overvoltages on power transmission lines with special reference to the overvoltage protection of low voltage networks," *Transactions of the Royal Institute of Technology*, Stockholm, Sweden, Nr. 120, 1958.
- [8] S.-C. Wu and W.-T. Hsiao, "Characterization of induced voltages on overhead power lines caused by lightning strokes with arbitrary configurations," *International Conference on Systems, Man, and Cybernetics*, Vol. 3, pp. 2706 - 2710, 1994.
- [9] R. Moini, V.A. Rakov, M.A. Uman, and B. Kordi, "An antenna theory model for the lightning return stroke," in proc. *International Zurich Symposium on Electromagnetic Compatibility*, pp. 149-152, Zurich, Switzerland, February 1997.
- [10] R. Moini, B. Kordi, V. A. Rakov, and G. Z. Rafi, "A new lightning return stroke model based on antenna theory," *J. Geophys. Res.*, No 105, pp. 29,693-29,702, 2000.
- [11] R. Moini, B. Kordi, and M. Abedi, "Evaluation of LEMP effects on complex wire structures located above a perfectly conducting ground using electric field integral equation in time domain," *IEEE Trans. EMC*, Vol. 40, No. 2, pp. 154-162, May 1998.
- [12] B. Kordi, R. Moini, and S.H.H. Sadeghi, "Comparison of the Transmission Line coupling model with the EFIE approach for lightning induced overvoltage prediction," in proc. *International Zurich Symposium on Electromagnetic Compatibility*, Zurich, Switzerland, February 1999.
- [13] M. Van Blaricum, "A numerical technique for the time-dependent solution of thin-wire structures with multiple junctions," *M.S. Thesis*, Electrical Engineering Department, University of Illinois, 1972.
- [14] E.K. Miller, A.J. Poggio, and G.J. Burke, "An integrodifferential equation for time-domain analysis of thin wire structure - part I," *J. Computational Physics*, 12, 24-48, 1973.
- [15] J.A. Landt, E.K. Miller, and M. A. Van Blaricum, "computer program for the time-domain electromagnetic response of thin wire structures," *Report UCRL 51585*, Lawrence Livermore Laboratory, Livermore, CA, 1974.
- [16] M.J. Master and M.A. Uman, "Transient electric and magnetic fields associated with establishing a finite electrostatic dipole," *Am. J. Phys.*, Vol. 51, No. 2, 1983.

SID

ابزارهای
پژوهش

سرویس ترجمه
تخصصی

کارگاه‌های
آموزشی

بلاگ
مرکز اطلاعات علمی

سامانه ویراستاری
STES

فیلم‌های
آموزشی

سامانه ویراستاری (ویرایش متون فارسی، انگلیسی، عربی)

کارگاه‌ها و فیلم‌های آموزشی مرکز اطلاعات علمی

روش تحقیق کمی

آموزش مهارت‌های کاربردی
در تدوین و چاپ مقالات ISI

آموزش نرم افزار Word
برای پژوهشگران